

Schematic	Package	Manufacturer	Description	Part Number	DigiKey Part	Qty	Notes
Resistors							
R1	0603 (1608 Metric)	Panasonic - ECG	RES SMD 560 OHM 1% 1/4W 0603	ERJ-PA3F5600V	P560BYCT-ND	1	560 resistor (red LED current limiting)
R2	0603 (1608 Metric)	Panasonic - ECG	RES SMD 1K OHM 1% 1/4W 0603	ERJ-PA3F1001V	P1.0KBYCT-ND	1	1k resistor (blue LED current limiting)
R3-4	0603 (1608 Metric)	Panasonic - ECG	RES SMD 2.2K OHM 1% 1/4W 0603	ERJ-PA3F2201V	P2.2KBYCT-ND	2	2.2k audio input resistor
R5	0603 (1608 Metric)	Panasonic - ECG	RES SMD 10K OHM 1% 1/4W 0603	ERJ-PA3F1002V	P10KBYCT-ND	1	10k resistor
R6-8	0603 (1608 Metric)	Panasonic - ECG	RES SMD 47K OHM 1% 1/4W 0603	ERJ-PA3F4702V	P47KBYCT-ND	3	47k resistor
Capacitors							
C1-2	0603 (1608 Metric)	Murata	3300pF ±10% 50V X7R Ceramic Capacitor	GRM188R71H332KA01D	490-1503-1-ND	2	3.3nF (3300pF)
C3	0603 (1608 Metric)	Murata	0.1µF ±10% X7R 50V Ceramic Capacitor	GRM188R71H104KA93D	490-1519-1-ND	1	0.1µF SPI Flash bypass cap
C4-5	0603 (1608 Metric)	Murata	1µF ±10% 16V X5R Ceramic Capacitor	GRM188R61C105KA93D	490-1536-1-ND	2	1µF audio input caps
C6	0805 (2012 Metric)	Murata	4.7µF ±10% 25V X5R Ceramic Capacitor	GRM21BR61E475KA12L	490-3335-1-ND	1	4.7µF bypass cap for LM48310 supply
C7-8	0805 (2012 Metric)	Taiyo Yuden	CAP CER 10µF 25V X5R 0805	TMK212BJ106KG-T	587-2985-1-ND	2	10µF input/output caps for voltage regulator
C9	0805 (2012 Metric)	Taiyo Yuden	47µF ±20% 6.3V X5R Ceramic Capacitor	JMK212BJ476MG-T	587-1779-1-ND	1	47µF additional for 5v supply
Voltage Regulator							
LDO	TO-261-4/SOT-223	ON Semi	IC REG LDO 5V 1A SOT223	NCP1117ST50T3G	NCP1117ST50T3GOSCT-ND	1	5V regulator.
LEDs							
D1	0805 (2012 Metric)	Lite-On, Inc	LED RED CLEAR 0805 SMD	LTST-C170CKT	160-1176-1-ND	1	Red, 1.8 fv, 10mA, 10mcd. Green dots represent anode (face away from bar).
D2	0805 (2012 Metric)	Kingbright	Blue 470nm LED Indication - Discrete 2.65V 0805 (2012 Metric)	APT2012LVBC/D	754-1938-1-ND	1	Blue, 2.65 fv, 2mA, 24mcd. Green dots represent cathode (face towards bar).
Connectors							
JP1-2	Connector	JST	3 Positions Header, Shrouded Connector 0.079" (2.00mm) Surfa	S3B-PH-SM4-TB(LF)(SN)	455-1750-1-ND	2	JST PH surface mount side entry for serial from TCB (3-pos)
JP3-5	Connector	JST	CONN HEADER XH TOP 2POS 2.5MM	B2B-XH-A(LF)(SN)	455-2247-ND	3	2 position header, voltage out passthrough to TCB (2), plus speaker
JP6	Connector	JST	3 Positions Header, Shrouded Connector 0.098" (2.50mm) Thro	B3B-XH-A(LF)(SN)	455-2248-ND	1	3 position header for volume control pot
JP7-11	Header	Banggood	2.54mm 3x40P Male Pins Three Row Right Angle Pin Header		972983	0.125	3x2 right angle RC connectors. Digikey doesn't have - buy from Banggood or HobbyKing.
JP12	Header	Sullins Connector	CONN HEADER .100" SNGL STR 20POS	PRPC020SAAN-RC	S1011EC-20-ND	0.1	20 position header - break apart for JP12
JP13-14	Socket	Sullins Connector	14 Position Header Connector 0.100" (2.54mm)	PPTC141LFBN-RC	S7012-ND	2	14 position female socket - for Teensy sides
JP15	Socket	Sullins Connector	5 Position Header Connector 0.100" (2.54mm)	PPTC051LFBN-RC	S6103-ND	1	5 position female socket - for Teensy back
Micro SD							
SD	MicroSD	Amphenol	CONN MICRO SD CARD PUSH-PUSH R/A	473340001	WM3288CT-ND	1	Adafruit footprint MICROSD
IC							
U1	WSON-10 (3x3)	Texas Instruments	IC AMP AUDIO PWR 2.6W MONO 10SON	LM48310SD/NOPB	LM48310SD/NOPBCT-ND	1	Class D, 2.6w @ 4ohm x1, 2.4v-5.5v. Same as used on PJRC Prop Shield
U2	8-SOIC	Winbond	IC FLASH 128MBIT 104MHZ 8SOIC	W25Q128JVSQ TR	W25Q128JVSQ CT-ND	1	16 MB SPI Flash memory
U3		PJRC	Teensy USB Development Board	TEENSY32		1	Teensy 3.2 from PJRC.com